|| Parallels[®]

How to specify UDP ports used by the "Apply OS X Image" Task Sequence step

• Parallels Device Management

Information

In <u>Parallels Mac Management v4.5 Update 1 for Microsoft SCCM</u> we added the ability to specify client UDP ports used by the **Apply OS X Image** Task Sequence step.

The Mac uses these ports to listen for traffic from the NetBoot server to receive a URL of system image to be downloaded during the Task Sequence.

This can be configured by the following steps:

- 1. In SCCM go to Assets and Compliance > Overview > Device Collections > right click on collection > Properties > Collection Variables tab.
- 2. Create **Collection Variable** or **Resource Variable** with the name **PmmOSDUdpPortRange** and value in the range format **StartPort-EndPort** (e.g. *65000-65500*) or single port format Port (e.g. *50000*).

© 2024 Parallels International GmbH. All rights reserved. Parallels, the Parallels logo and Parallels Desktop are registered trademarks of Parallels International GmbH. All other product and company names and logos are the trademarks or registered trademarks of their respective owners.